



CABINET HARDWARE SYSTEMS

ZAPPHYRE DRAWER SYSTEM

#ZDS

Australia

1800 008 591 ■ www.artia.com.au

VICTORIA:

235 Settlement Road,
Thomastown VIC 3074

NEW SOUTH WALES:

6 Nello Place,
Wetherill Park NSW 2164

QUEENSLAND:

Building 2/660 MacArthur
Avenue, Pinkenba QLD 4008

SOUTH AUSTRALIA:

13 Rosberg Road,
Wingfield SA 5013

WESTERN AUSTRALIA:

Unit 5/1 Dellamarta Road,
Wangara WA 6065

New Zealand

0800 267 625 ■ www.artia.co.nz

AUCKLAND:

11 Bruce Roderick Drive,
East Tamaki, Auckland 2013

CHRISTCHURCH:

117 Wrights Road,
Addington, Christchurch 8024

DRAWER SYSTEMS

ZAPPHYRE DRAWER SYSTEM

► To configure your Zaphyre Drawer System 1.1

Z1 Choose your **base set** by drawer length.



Base set contents

- Pair of drawer sides
- Pair of drawer slides
- Pair of cover plates
- Installation instructions

Base sets are available in **six lengths** as

- NL270
- NL350
- NL400
- NL450
- NL500
- NL550

[ZDS1.270G.W](#)

[ZDS1.350G.W](#)

[ZDS1.400G.W](#)

[ZDS1.450G.W](#)

[ZDS1.500G.W](#)

[ZDS1.550G.W](#)

Z2 Pick from **two types** of all metal **front-fixing brackets**.



To suit your production processes, select from

- Screw-in front brackets
- Expanding dowel front brackets

[ZDS2.201M.S](#)

[ZDS2.320M.ED](#)

- *Supplied as each, two required per drawer*

Z3 Select from **four drawer heights**.



Choice of rear brackets (supplied as set of LH/RH)

- **H84** – To create a standard drawer
- **H135** – For a lower mid-height drawer (with a single set of rails)
- **H167** – For a mid-height pot drawer (with a single set of rails)
- **H199** – For a tall pot drawer with a single or double set of rails, or solid glass sides

[ZDS3.32084.W](#)

[ZDS3.32135.W](#)

[ZDS3.32167.W](#)

[ZDS3.32199.W](#)

DRAWER SYSTEMS

ZAPPHYRE DRAWER SYSTEM

Z4 Pick your pot drawer configuration.

- Decide on the **type and number** of **gallery rails** - available across ALL lengths
 - Square rails** - with choice of dowel or screw-fixing

ZDS4.[SQR270D.W](#)
ZDS4.[SQR350D.W](#)
ZDS4.[SQR400D.W](#)
ZDS4.[SQR450D.W](#)
ZDS4.[SQR500D.W](#)
ZDS4.[SQR550D.W](#)

- Round rails** - dowel fixing (*only*)

ZDS4.[RRM270D.W](#)
ZDS4.[RRM350D.W](#)
ZDS4.[RRM400D.W](#)
ZDS4.[RRM450D.W](#)
ZDS4.[RRM500D.W](#)
ZDS4.[RRM550D.W](#)

- Instead of gallery rails, you can choose from **two solid side options**

- Own design 8mm thick panels (i.e. 6mm board laminated both sides)
- Side-walls in frosted safety glass (NL400 to NL550)

ZDS5.[IGCS199.W](#)

ZDS5.[IGCS199.W](#) with ZDS5.[IGP199***.G](#)

ZDS5.[IGP199400.G](#)
ZDS5.[IGP199450.G](#)
ZDS5.[IGP199500.G](#)
ZDS5.[IGP199550.G](#)

Z5 For installation behind a door, customise your Zephyre Drawer System as a pantry or inner drawer, adding to **Z1** and **Z3** options



- Standard height H84 inset drawer
- Tall H199 inset drawer with choice of
 - Front railing **bar**
 - Solid front **insert** panel
- PLUS** choice of

ZDS5.[IFC84.W](#) / ZDS5.[IFP1200.W](#)

ZDS5.[IFCB199.W](#) / ZDS5.[IFB1200.W](#) / ZDS5.[IFP1200.W](#)

ZDS5.[IFC199.W](#) / ZDS5.[IFIP200.W](#) / ZDS5.[IFP1200.W](#)



- own design sides (8mm) with front **clip**
- frosted **glass** sides
- square** gallery rails (screw-fix)

ZDS5.[IGCS199.W](#)

ZDS5.[IGCS199.W](#) with ZDS5.[IGP199***.G](#)


ZDS4.[SQR***D.W](#)

DRAWER SYSTEMS

ZAPPHYRE DRAWER SYSTEM

Technical Information

Back panel dimensions




Back panel dimensions

- 16mm board
- Width = LW-87mm
- Height = As per above


Slide runner dimensions

• Ø4mm self-tapping screws recommended



* Dimensions for inner drawer installation

Drawer installation



Legend

KB Cabinet width LW Internal cabinet width NL Nominal length


All dimensions in millimetres

DRAWER SYSTEMS

ZAPPYRE DRAWER SYSTEM

► Installation Information


Cabinet space requirement




* Minimum required space for inner drawers

Base panel dimensions


- 16mm board
- Width = LW-75mm
- Length = NL-24mm




NL Nominal Length (i.e. NL500)
LW Internal cabinet width
D Front panel coverage




Front panel hole positions



Drawer removal



Inner drawer front panel installation




DRAWER SYSTEMS


ZAPPYRE DRAWER SYSTEM

► Technical Information


Drawer installation




Adjustment



- ± 2 mm adjustment left/right
- Make sure to adjust both sides evenly




- **3** After adjustment, ensure to lock the screws




- **1** Unlock the front panel
- **2** ± 2 mm adjustment up/down

Tall inner drawer with front railing bar installation



- X Cutting dimension for internal front panel = LW-90
- Y Cutting dimension for square railing bar = LW-92
- LW Internal cabinet width

Tall inner drawer with solid front installation



- Z Cutting dimension for solid insert plate = LW-98
- LW Internal cabinet width

Legend

KB	Cabinet width	LW	Internal cabinet width	NL	Nominal length
-----------	---------------	-----------	------------------------	-----------	----------------


All dimensions in millimetres

DRAWER SYSTEMS


ZAPPHYRE DRAWER SYSTEM

► Installation Information


Side railing installation (round & square)



Glass side panel installation



Front panel removal





CABINET HARDWARE SYSTEMS

ZAPPHYRE DRAWER SYSTEM

Version 1.1

Australia

1800 008 591 ■ www.artia.com.au

VICTORIA:

235 Settlement Road,
Thomastown VIC 3074

NEW SOUTH WALES:

6 Nello Place,
Wetherill Park NSW 2164

QUEENSLAND:

Building 2/660 MacArthur
Avenue, Pinkenba QLD 4008

SOUTH AUSTRALIA:

13 Rosberg Road,
Wingfield SA 5013

WESTERN AUSTRALIA:

Unit 5/1 Dellamarta Road,
Wangara WA 6065

New Zealand

0800 267 625 ■ www.artia.co.nz

AUCKLAND:

11 Bruce Roderick Drive,
East Tamaki, Auckland 2013

CHRISTCHURCH:

117 Wrights Road,
Addington, Christchurch 8024